

1 Wireless Code Reader HD3900



HD3900 is a multifunctional reader with CMOS sensor for reading QR, Aztec and other codes, both printed and on screens. Possible applications include stores, markets, offices, warehouses. Wireless and free operation is ensured by radio communication, which is done through the included USB micro-receiver.

Wireless Code Reader HD3900

Model	HD3900	Compatible with the operating system	Linux, Android, Windows XP, 7, 8, 10, MacOS
Matrix	640*480 CMOS	Dimensions of the device	16,5 x 8,6 x 6,6 cm
Scanning method	Manual (on the button) / automatic (after approaching the code)	Package dimensions	18,5 x 11 x 8,3 cm
Confirmation of scanning	sound and light signal	Weight of the device	173 g
Scanning angle	Rotation $\pm 360^\circ$, horizontal $\pm 60^\circ$, oblique $\pm 70^\circ$	Weight of the device in the package	312 g
Memory capacity	storage of up to 120 thousand scanned codes	Operating temperature	10 to 45°C
Operating time on a single charge	15 hours	Storage temperature	-20 to 40°C
Full charge time	4 hours	Operating humidity	5 to 95%
Interface	USB	Storage humidity	5 to 95%
Readable 1D codes	Airline 2 of 5, Codabar, Codablock A, Code 128, Code 11, Code 32, Code 39, Code 93, EAN/UPC, EAN-8, EAN-13, Full ASCII Code 39, GS1 DataBar Expanded, GS1 DataBar Limited, GS1 DataBar Omnidirectional, HongKong 2 of 5 (China post), Interleaved 2 of 5, RSS-14, RSS-LIMITED, RSS-EXPANDED, Straight 2 of 5 Industrial, Telepen, Trioptic Code, UPC-A, UPC-E, MSI, Pharmacode, Matrix 2 of 5, Codablock F		
Readable 2D codes	Data Matrix Code, HANXIN, Maxicode, MicroPDF417, QR Code, Aztec Code, Composite, DOT_CODE		

