

## Wireless Barcode Reader HD3900

1



**The HD3900 is a multifunctional CMOS reader for reading QR codes, Aztec and other codes, both printed and on screens. Possible applications are shops, markets, offices, warehouses.**

Wireless and free operation is ensured by radio communication, which takes place via a USB microreceiver connected to the set.

## Wireless Barcode Reader HD3900

<b>Model</b>	HD3900	<b>Operating System Compatible</b>	Linux, Android, Windows 10/11, MacOS
<b>Matrix</b>	640*480 CMOS	<b>Device dimensions</b>	16.5 x 8.6 x 6.6cm
<b>Scanning method</b>	Manual/Automatic	<b>Dimension</b>	18.5x 11 x8.3cm
<b>Scan confirmation</b>	sound and light signal	<b>Weight of the device</b>	173g
<b>Scan angle</b>	Rotation $\pm 360^\circ$ , horizontal $\pm 60^\circ$ , $\pm 70^\circ$ slant	<b>Weight of the device in the package</b>	312 g
<b>Storage capacity</b>	Up to 120 thousand scanned codes are stored	<b>Operating Temperature</b>	10 to 45°C
<b>Work time; y on one Charging</b>	15hrs	<b>Temperature Stores</b>	-20 to 40°C
<b>Time to fully charge</b>	4 hours	<b>Device dimensions</b>	375 mm (W) x 268 mm (D) x 525 mm (H)
<b>Work Volume</b>	55 dB	<b>Operating humidity</b>	5 to 95%
<b>Interface</b>	USB	<b>Storage Humidity</b>	5 to 95%
<b>Readable 1D codes</b>	Airline 2 of 5, Coda bar, Codablock A, Code 128, Code 11, Code 32, Code 39, Code 93, EAN/UPC, EAN-8, EAN-13, Full ASCII Code 39, GS 1 DataBar Expanded, GS 1 Data Bar Limited, GS 1 DataBarOmnidirectional, Hong Kong 2 of 5 (China post), Interleaved 2 of 5, RSS-14, RSS-LIMITED, RSS-EXPANDED, Straight 2 of 5 Industrial, Telepen, T rioptic Code, UPC-A, UPC-E, MSI, Pharmacode, Matrix 2 of 5, Codablock F		
<b>Codes read 2D</b>	Data Matrix Code, HANXIN, Maxicode, MicroPDF417, QR Code, Aztec Code, Composite, DOT CODE		