

# Power supply for access control SecureEntry-PS10-3A



**SecureEntry-PS10-3A is a powerful and secure power supply designed for** Power supply for access control devices. It offers an output current of 3A **and works with devices with DC12V. It can be successfully** connect to electric lock, RFID reader, time recorder, or even an entire access control system.

# Access control power supply SecureEntry-PS10-3A

<b>Model</b>	SecureEntry-PS10-3A	<b>Holding time</b>	typical value at full load is 200 ms
<b>Device type</b>	power supply for access control devices	<b>Peak value</b>	100mVp-p typical value
<b>Input current</b>	AC100-240V	<b>Overload protection</b>	all output terminals are short-circuit protected
<b>Input frequency</b>	50~60Hz	<b>Opóźnienie blokady elektrycznej</b>	0-10 s
<b>Output voltage</b>	DC12V	<b>Dimensions of the device</b>	13x7,5x5 cm
<b>Output current</b>	3A	<b>Package dimensions</b>	13,6x8,5x6,3 cm
<b>Output current tuning range</b>	+/- 10% ~ +/- 15%	<b>Weight of the device</b>	300 g
<b>Charging stability</b>	1% of typical value	<b>Weight with packaging</b>	400 g
<b>Output stability</b>	0.5% of typical value	<b>Operating temperature</b>	-20°C - 65°C

