User manual

Monitor and laptop stand

SolidHand-AI01M01

Table of contents

Specification:

- **Warranty:** 1 year
- **Color:** matte black
- **Construction material:** steel, plastic
- **Surface finish:** powder coating
- **Number of monitors:** 1
- **Min. monitor diagonal:** 17"
- **Max. monitor diagonal:** 32"
- **VESA standard:** 75x75, 100x100
- **Laptop size:** 10" – 15,6"
- **Monitor weight:** 9 kg
- **Laptop weight:** 4 kg
- **Arm rotation range:** +90° ~ –90°
- **Monitor rotation range:** +180° ~ –180°
- **Monitor tilt range:** +45° ~ –45°
- **Max arm reach:** 376 mm
- **Pole height:** 407 mm
- **Handle dimensions:** 959 x 319 x 561 mm
- **Package dimensions:** 440 x 290 x 120 mm
- **Weight of the device:** 4.86 kg
- **Weight of handle with packaging:** 5.6 kg

Kit contents:

- Monitor mount,
- screws and mounting washers,
- user manual.

Features:

- **Number of monitors to be mounted**: 1
- **Number of laptops** to be mounted: 1
- **Arm rotation range**: +90° ~ –90°
- **Monitor weight**: 9 kg
- **Laptop weight**: 4 kg

Installation tips

CAUTION: Using the product with a load greater than the indicated allowable load may lead to instability, resulting in possible injury.

Please strictly follow the installation instructions. Improper installation may cause damage or serious personal injury.

Use proper safety equipment and proper tools. This product should only be installed by professionals.

Ensure that the supporting surface will safely support the total weight of the equipment and all included mounting hardware and components.

Use the included mounting screws and **DO NOT over** tighten the mounting screws.

The product contains small parts that may pose a choking hazard if swallowed. Keep these components away from children.

This product is intended for indoor use only. Using this product outdoors may lead to product failure and personal injury.

IMPORTANT: Make sure you have received all parts according to the component list before installation. If any parts are missing or defective, please contact us.

Installation

1

ø10-60mm

10-40mm

OR

ø 10mm (ø 3/8")

10-40mm

10-35mm

OR

35-60mm

2

±180°

Tighten the limiting screw (do not over tighten).

Arm can rotate without stopping.

1 5mm

2 ±90°

Tighten the limiting screw (do not over tighten).

Arm can rotate 180°.

3

4

✓ ✗ Too long Too short

M-A
M-B
M-C

3mm

TOP

5

6

7

CAUTION: DO NOT loosen the screws counter-clockwise, or it may cause damage to the product. If the arm drops or rises, tighten the screws as shown.

8

Note: If the display does not stop at your desired position, tighten the screw as shown.