

Manual

Platform warehouse
scale up to 800 kg
wagPRO-P800

Table of contents

Specifications:.....	2
Set contents:.....	3
General comments	4
Features.....	4
First run	5
Operations.....	5

Specifications:

- **Material:** Steel
- **Maximum nominal load:** 800 kg
- **Accuracy:** +/- 200 g
- **Maximum permissible load:** 100% of nominal load
- **Scale Legalization:** No
- **Display:** Digital, up to 5 digits
- **Display backlight:** Green
- **Additional functions:** weight tare, product counting, unit price entry, screen backlight, automatic switch-off function
- **Battery type:** lead-acid
- **Power supply:** mains, rechargeable
- **Battery capacity:** 4 Ah (4000 mAh)
- **Battery life:** up to 2 days
- **Standby time:** up to a week
- **Auto Backlight Dimming:** After 10 seconds of inactivity
- **Operating temperature:** 0 to 40°C
- **Operating humidity:** 0 to 85%
- **Device dimensions:** 80 (L) x 60 (W) x 84 (H) cm
- **Dimensions of the weighing platform:** 60 x 80 cm
- **Device weight:** 28.75 kg
- **Package weight:** 28.6 kg

Set contents:

- Platform scale scalePRO-P800
- Mounting screws
- AC Adapter
- Manual

General comments

- Please keep the scale dry, do not expose it to direct sunlight, do not store it in places with too high or too low temperature, high humidity, high dust or in places exposed to strong shocks.
- Do not overload the platform with heavy objects, as this may damage the load cell.
- If goods exceed the maximum capacity are placed on the scale, the scale will display "FULL" and sound an alarm. In such a case, it is necessary to remove the goods immediately.
- The scale should work with a stable voltage, higher or lower voltage can cause problems.
- The scale works on AC power. Unplug if the scale will not be used for a long time.
- Use a damp cloth to clean the scale, do not immerse it in water, as this may cause a short circuit.
- Keep the scale clean and dry.

Features

- **Power supply:** AC 230V or 110V and DC 4V or 6V (built-in battery), the scale can work while the battery is charging.
- **Accumulation Operation** (1-99 times)
- **Operating temperature:** 0°C - 40°C
- **Operating Humidity:** <85%

Displays:

- Scale display - 5 digits
- Unit price display: 5 digits
- Total price display: 6 digits

First run

- Remove the device from the package, remove the platform, stainless steel pole, display indicator, and place the scale on a flat surface.
- Tighten the post to the platform.
- Adjust the four feet under the platform.
- To connect the meter wire to the wire coming out of the platform (connecting 2 plugs from these 2 wires), then fix the meter to the pole. This will ensure that when you turn on the switch, the scale will work properly.

Operations

- Make sure the scale is on a flat, stable surface, and then turn it on.
- When the balance is turned on, **the ZERO** and **STAB** functions are activated. Before weighing the goods, make sure that both **ZERO** and **STAB** are visible on the display, otherwise you will not get the correct measurement value.
- **Backlight button:** Press this button to turn on the backlight of the LCD display. Press it again to turn off the backlight. When the LCD backlight is turned on, if there is no object on the platform, the backlight will automatically turn off after 3 seconds to save power.
- **ZERO button:** resets the value in the balance window (if the TARE function is active, the ZERO function is disabled).
- **TARE button:**

To activate the TARE function: Press this button and the TARE indicator will display and the scale window will show 0.000

To disable the TARE function: after removing the item, the scale screen will show a negative value, then press the **TARE button**, the arrow will indicate **ZERO**, and the scale screen will indicate 0, which means the TARE function has been disabled.

- **[0]-[9] key:** The number key (0-9) is used to set the unit price.
- **Add key:** During weighing, saves and sums the value of the weight and quantity.

Once the goods are placed on the platform, the measurement will appear on the screen. You can press the number key to enter the unit price, and the total price screen will display the first item. Now, if you press **ADD**, the unit price will appear: **Add: 1**

Delete the item, place another item, press the number key to enter the unit price, and then the three windows display the new values, and the **total price** window displays the amount for the second item.

Press the Add button again and the "Add 2" unit price window will appear.

Now the total price window shows the value for 2 units. If you want to weigh more pieces, you can repeat this step as many times as you want.

Note: The total number of pieces should not exceed 99.

If you want to cancel this feature, simply press **the C button** on the panel.

- **The C: button** is used to cancel the set unit price.
- **DECIMAL POINT button:** Used to set the decimal position of the unit price.

- **M*(*=1.2, etc.) key:** Displays the unit price stored in memory. When you place the item on the platform and press one of the keys, the unit price and the corresponding total price will be displayed on the screen.
- **Store key:** Used to save the unit price using the M* key. First, press the STORE key, the unit price will be displayed as "o", then you can enter the desired digits and press the M*(*=1.2, etc.) key, after which the price will be saved.